


ShieldPro Motion Sensor Quick Start Guide

What comes in the box?

- Motion sensor x 1
- 3V Lithium battery x 1
- Wall screws x 3
- Wall anchors x 3


Motion sensor parts and features

Figure 1: Outside of the sensor



1. Pairing button
2. Back casing
3. Security screw

Figure 2: Inside the sensor (under back casing)



4. Pet Pins
5. Distance (SENS) Pins
6. Battery

Placement tips

- Indoor use only.
- Pair with the panel before mounting.
- Place 6-7 feet above the ground.
- To prevent false alarms, do not install near any heat sources.
- Before mounting, see the **Pin Guide**.

Mount your motion sensor

Step 1 Clean and dry the location for the sensor.

Step 2 Remove all battery tabs.

Step 3 Pair with the panel.

Settings (☰ button) > **Devices** > + > **Motion** > Follow the prompts to pair the sensor.

Step 4 Peel the backing off the sticker and press the sensor on to the wall. Only press on the hard plastic sensor casing.

Pin Guide

Your motion sensor has two separate configuration options:

1. **Pet size pins** - This can help reduce false alarms caused by pets.

Note: These are NOT exact weights. The closer a pet gets to the motion detector, the more likely they will trigger an event despite its size and the pin configuration.

2. **Distance pins** - Adjust the coverage distance of the motion sensor.

Pet pins

Pet size	Jumper placement	Pins
Pets up to 33 pounds	Cover: Top and middle pin Expose: Bottom pin	
Pets up to 55 pounds (Default setting)	Cover: Bottom and middle pin Expose: Top pin	

Distance (SENS) pins

Coverage distance	Jumper placement	Pins
Low (13 feet)	Cover: Top and middle pin Expose: Bottom pin	
High (26 feet) (Default setting)	Cover: Bottom and middle pin Expose: Top pin	

How to adjust the configuration pins

- Step 1** If the motion sensor is active, bypass it in your security panel.
- Step 2** Remove the security screw and back casing.
- Step 3** Pull the black plastic jumper straight up to remove it from the pins. You will see 3 pins.
- Step 4** Replace the jumper by pushing straight down, covering the desired pins (see **Pin Guide**).
- Step 5** Return sensor to back casing. Press on the hard plastic until it clicks in place. Secure with the security screw.
- Step 6** If bypassed, reactivate the sensor in the panel.

Questions?

Contact us at 1-800-574-7798 or CST@shieldpro.com